- IDIS

DR-1204P

- Total incoming throughput 84Mbps
- Up to 120ips Full HD real-time recording
- Up to 120ips live display
- Easy to install, set-up, and play with DirectIP cameras
- Built-in 4 channel PoE Switch
- Expandable up to 4TB
- Supports one click network configuration through FEN service




SPECIFICATIONS

IDEO	
ideo Inputs	4 IP Channels
Max. Incoming Throughput	84Mbps
upported Camera	
ideo Outputs	1 HDMI, 1 VGA
isplay Resolution	1920 x 1200, 1920 x 1080, 1680 x 1050, 1600 x 1200
isplay Speed	Up to 120ips
ligital Zoom	x2 ~ x12
ECORDING	
Max. Throughput	32Mbps, 120ips @ Full HD
ecording Resolution	Up to 5MP (Depending on IP Camera)
compression	H.264, H.264 with IDIS Intelligent Codec
ecording Mode	Time-lapse, Event, Pre-event, Panic
rigger Events	Alarm In, Audio Detection, Motion Detection, Trip Zone, Tampering, Video Loss
LAYBACK	
erformance	4ch Full HD Synchronous Playback
earch Mode	Time-lapse, Event Log, Thumbnail, Motion, Text-in
igital Zoom	x2 ~ x12
TORAGE	
IDD	SATA x 1 (Up to 4TB Capacity for Each Disk)
otal Capacity	4TB = 4TB x 1
IETWORK	
lient Connection	Fast Ethernet (Client) x 1
ideo In Connection	Fast Ethernet (IP Camera) x 4
ransmission Speed	20Mbps / 50Mbps (BRP Mode)
amera Power	PoE (IEEE 802.3at Class 4) Supported 4 Ports, 30W
emote Data Export	IDIS Player, AVI, JPG
vent Notification	Email (Attach Clip (.cbf) .MP4), Callback to Remote S/W, Push Notification (IDIS Mobile), SNS (Twitter)
wo-way Audio	Yes
lient Viewer	IDIS Center, IDIS Mobile, IDIS Web, IDIS Solution Suite
NTERFACE	,
udio In / Out	Local (NVR) : - / 1 HDMI IP Camera : 4 / 4 (Depending on IP Camera)
larm In / Out	Local (NVR) : - / - IP Camera : 4 / 4 (Depending on IP Camera)
larm Reset In	-
erial Interface	
ISB	USB 2.0 x 2
Iser Interface	Mouse, Network Remote Keyboard
ENERAL	
perating System	Embedded Linux
Init Dimensions (W x H x D)	215mm x 214.5mm x 48.5mm (8.5" x 8.5" x 1.9")
Init Weight	1.2kg (2.7lb) (With 1 HDD)
Vorking Temperature	0°C to 40°C (32°F ~ 104°F)
perating Humidity	0% ~ 90%
ower Input	DC 56V 1.17A
•	39.2W (for NVR), Max. 30W (for PSE)
ower Consumption	

DIMENSIONS

(Unit - mm)







- 1 Factory Reset Button
- 2 HDMI
- 3 VGA Out Port
- 4 USB5 Network Port
- 6 Video In RJ45
- Power In Port